
Gira G1 Release Notes

Firmware version: 3.2.148
Date 25/05/2020

Gira Project Assistant (GPA) version: 4.2 or higher
We recommend that you always use the latest available GPA version.

ETS configuration and start-up

Configuration and start-up of the device require the start-up software certified by the KNX Association, version ETS5.4 or higher. No product database is available for older versions of the ETS. For ETS start-up of the Gira G1 with firmware version 3.2, the ETS application 3.0 must be used. Older ETS applications are incompatible with firmware version 3.2 and cannot be converted.

Please note the instructions for updating existing devices on the next page.

Note

The password on the device website will sometimes no longer work after updating older Gira G1 (without FDSK sticker).
In this case, the password for the Gira G1 must be reassigned in the Maintenance Centre of the Gira Project Assistant.

New functions

- KNX Secure support
- Signalling/ring tone even without Türko system via KNX

Bugs fixed

- Display may not darken
- The demo of the Door Communication application does not work in demo mode
- The room temperature display in the status bar does not disappear
- Audio control: Volume may automatically adjust to 0
- Heating/cooling switchover in heating operation (cyclical heating command ensures deactivation of heating)
- Relative dimming after restart (without status) not possible
- Different translations

Known HomeServer Client restrictions

- No timer configuration
- Direct plug-in switchover (plug-ins are only available via menu tiles)
- Diagram plug-in: Switchover hour/day/week/month/year
- Camera plug-in: Display of buttons
- Call of third-party apps (e.g. Revox)
- Menu entries "shake" and "clicking sound" have no function

Updating a configured Gira G1 in the ETS 5



Note

The procedure described here only works in ETS 5.

To update an existing Gira G1 in a project, please proceed as follows after the firmware update:

- 1 Open the project in the ETS.
- 2 Import the new ETS product file of the Gira G1 into the device catalogue.
- 3 Open the project in which the Gira G1 you want to update is located.
- 4 Insert a Gira G1 with the new program version into the project parallel to the existing Gira G1.
- 5 Select the already configured Gira G1 with the old program version and open the "Information" tab in the right-hand column of the ETS and then the "Application program" tab.
 - ✓ Two options are available here:
 - Change application program**
Important: Do not open the selection list!
If you select the new version of the application program from the selection list here, all settings and configurations are reset!
 - Update application program version**
When you click on the "Update" button, only the new functions are added to the configured device. The existing configuration is retained.
- 6 Click on the "Update" button.
- 7 The new parameters of the new program version are added to the Gira G1.
- 8 The new parameters can then be configured and transferred to the device via start-up.

